

TSE ANKARA LABORATORIES  
CALIBRATION ACCREDITATION SCOPE

MEASURAND /DEVICE	MEASURING RANGE	CONDITIONS	MEASUREMENT CAPABILITY / UNCERTAINTY	NOTES
<b>ELEKTRİK</b>				
<b>DC VOLTAGE (&lt; 1000 V)</b> <b>DC VOLTAGE</b> <b>Source:</b> DC VOLTAGE Source Calibrator: DC	$100 \mu V \leq U < 100 mV$ $100 mV \leq U < 1V$ $1 V \leq U \leq 10V$ $10 V < U \leq 100V$ $100 V < U \leq 1000V$		$2,5 \cdot 10^{-5} U + 2 \mu V$ $7 \cdot 10^{-6} U + 20 \mu V$ $6 \cdot 10^{-6} U + 7 \mu V$ $8,5 \cdot 10^{-6} U + 110 \mu V$ $8 \cdot 10^{-6} U + 900 \mu V$	With 3458A
<b>DC VOLTAGE (&lt; 1000V)</b> <b>DC VOLTAGE</b> <b>Source:</b> DC VOLTAGE Source Calibrator: DC	$10 mV$ $100 mV$ $1 V$ $10V ,100V ,1000V$		$1,0 \cdot 10^{-4} \cdot U$ $1,5 \cdot 10^{-5} \cdot U$ $4,0 \cdot 10^{-6} \cdot U$ $2,0 \cdot 10^{-6} \cdot U$	With Reference DC VOLTAGE Standard + VOLTAGE Divider
<b>DC VOLTAGE (&lt; 1000V)</b> <b>DC VOLTAGE</b> <b>Monitors:</b> Multimeter: DC VOLTAGE DC Voltmetre	$100 \mu V \leq U < 220 mV$ $220 mV \leq U \leq 2,2 V$ $2,2 V < U \leq 11 V$ $11 V < U \leq 22 V$ $22 V < U \leq 220 V$ $220 V < U \leq 1000 V$		$2 \cdot 10^{-5} \cdot U + 2 \mu V$ $1 \cdot 10^{-5} \cdot U + 5 \mu V$ $1 \cdot 10^{-5} \cdot U + 25 \mu V$ $1 \cdot 10^{-5} \cdot U + 90 \mu V$ $1 \cdot 10^{-5} \cdot U + 300 \mu V$ $1 \cdot 10^{-5} \cdot U + 3 mV$	With 5700A
<b>DC VOLTAGE (&lt; 1000V)</b> <b>DC VOLTAGE</b> <b>Monitors:</b> Multimeter: DC VOLTAGE DC Voltmetre	$10 mV$ $100 mV$ $1 V$ $10V ,100V ,1000V$		$1,2 \cdot 10^{-4} \cdot U$ $1,2 \cdot 10^{-5} \cdot U$ $4,0 \cdot 10^{-6} \cdot U$ $2,0 \cdot 10^{-6} \cdot U$	With Reference DC VOLTAGE Standard + VOLTAGE Divider

TSE ANKARA LABORATORIES  
CALIBRATION ACCREDITATION SCOPE

MEASURAND /DEVICE	MEASURING RANGE	CONDITIONS	MEASUREMENT CAPABILITY / UNCERTAINTY	NOTES
<b>DC Current (&lt; 100 A)</b> <b>DC Current Source:</b> DC Current Source Calibrator: DC Current Transconductance Amplifier	$100 \mu\text{A} \leq I \leq 1 \text{ mA}$ $1 \text{ mA} < I \leq 10 \text{ mA}$ $10 \text{ mA} < I \leq 100 \text{ mA}$ $100 \text{ mA} < I \leq 1 \text{ A}$  $100 \mu\text{A} \leq I < 1 \text{ mA}$ $10 \text{ mA} < I \leq 1 \text{ A}$ $1 \text{ A} < I \leq 10 \text{ A}$ $10 \text{ A} < I \leq 15 \text{ A}$ $15 \text{ A} < I \leq 20 \text{ A}$  $10 \text{ A} < I \leq 150 \text{ A}$ $150 \text{ A} < I \leq 550 \text{ A}$ $550 \text{ A} < I \leq 1025 \text{ A}$		$3,5 \cdot 10^{-5} \cdot I + 10 \text{ nA}$ $3,5 \cdot 10^{-5} \cdot I + 150 \text{ nA}$ $5,5 \cdot 10^{-5} \cdot I + 1 \mu\text{A}$ $1,5 \cdot 10^{-4} \cdot I + 25 \mu\text{A}$  $1 \cdot 10^{-5} \cdot I$ $2 \cdot 10^{-5} \cdot I$ $6,5 \cdot 10^{-5} \cdot I + 140 \mu\text{A}$ $8,5 \cdot 10^{-5} \cdot I$ $1,2 \cdot 10^{-4} \cdot I$  $2,8 \cdot 10^{-2} \cdot I + 0,82 \text{ A}$ $2,8 \cdot 10^{-2} \cdot I$ $2,5^{-2} \cdot I$	With 3458A DMM  With Current Shunt  With Fluke 376
<b>DC Current (&lt; 100 A)</b> <b>DC Current Monitors:</b> Multimeter: DC Current DC Ammeter Clampmeter	$100 \mu\text{A} \leq I < 220 \mu\text{A}$ $220 \mu\text{A} \leq I < 2,2 \text{ mA}$ $2,2 \text{ mA} \leq I < 22 \text{ mA}$ $22 \text{ mA} \leq I < 220 \text{ mA}$ $220 \text{ mA} \leq I \leq 2,2 \text{ A}$  $2,2 \text{ A} < I \leq 11 \text{ A}$ $11 \text{ A} < I \leq 20 \text{ A}$  $100 \mu\text{A} \leq I \leq 10 \text{ mA}$ $10 \text{ mA} < I \leq 1 \text{ A}$ $1 \text{ A} < I \leq 10 \text{ A}$ $10 \text{ A} < I \leq 15 \text{ A}$ $15 \text{ A} < I \leq 20 \text{ A}$  $10 \text{ A} \leq I \leq 1000 \text{ A}$		$9 \cdot 10^{-5} \cdot I + 15 \text{ nA}$ $6 \cdot 10^{-5} \cdot I + 25 \text{ nA}$ $6 \cdot 10^{-5} \cdot I + 250 \text{ nA}$ $7 \cdot 10^{-5} \cdot I + 2.5 \mu\text{A}$ $1,3 \cdot 10^{-4} \cdot I + 45 \mu\text{A}$  $6 \cdot 10^{-4} \cdot I$ $4 \cdot 10^{-4} \cdot I$  $1 \cdot 10^{-5} \cdot I$ $2 \cdot 10^{-5} \cdot I$ $6,5 \cdot 10^{-5} \cdot I + 140 \mu\text{A}$ $8,5 \cdot 10^{-5} \cdot I$ $1,2 \cdot 10^{-4} \cdot I$  $5 \cdot 10^{-3} \cdot I$	With 5700A  With 5520A With 5700A + 5220A With Current Clampmeter Calibration ( With 5520A + 50 Turn Coil

TSE ANKARA LABORATORIES  
CALIBRATION ACCREDITATION SCOPE

MEASURAND /DEVICE	MEASURING RANGE	CONDITIONS	MEASUREMENT CAPABILITY / UNCERTAINTY	NOTES	
<b>DC Resistance</b>	100 $\mu\Omega$	I <sub>max</sub> = 60 A	5.10 <sup>-3</sup> .R	R = Measured Value	
<b>DC Resistance</b>	1 m $\Omega$	I <sub>max</sub> = 30 A	7.10 <sup>-5</sup> .R		
<b>Measuring Instruments:</b>	10 m $\Omega$	I <sub>max</sub> = 20 A	5.10 <sup>-5</sup> .R	With Reference Resistors	
Multimeter:	100 m $\Omega$	I <sub>max</sub> = 1 A	2.10 <sup>-5</sup> .R		
Microohmmeter	1 $\Omega$	I <sub>max</sub> = 0,32 A	5.10 <sup>-6</sup> .R		
Insulation	10 $\Omega$	I <sub>max</sub> = 0,1 A	5.10 <sup>-6</sup> .R		
Resistance Tester	100 $\Omega$	I <sub>max</sub> = 32 mA	5 10 <sup>-6</sup> .R		
	1 k $\Omega$	I <sub>max</sub> = 10 mA	5.10 <sup>-6</sup> .R		
	10 k $\Omega$	I <sub>max</sub> = 3,2 mA	5.10 <sup>-6</sup> .R		
	100 k $\Omega$	I <sub>max</sub> = 1 mA	5.10 <sup>-6</sup> .R		
	1 M $\Omega$	V <sub>max</sub> = 320 V	1.10 <sup>-5</sup> .R		
	10 M $\Omega$	V <sub>max</sub> = 1000 V	1,5.10 <sup>-5</sup> .R		
	100 M $\Omega$	V <sub>max</sub> = 1000 V	2,5.10 <sup>-5</sup> .R		
	0,1 $\Omega$ ≤ R < 1 $\Omega$	I <sub>max</sub> = 2 A	8.10 <sup>-4</sup> .R		
	1 $\Omega$ ≤ R ≤ 100k $\Omega$	1 $\Omega$ -10 $\Omega$ (I <sub>max</sub> = 600 mA) 10 $\Omega$ -100 $\Omega$ (I <sub>max</sub> = 200 mA) 100 $\Omega$ -1 k $\Omega$ (I <sub>max</sub> = 60 mA) 1 k $\Omega$ -10 k $\Omega$ (I <sub>max</sub> = 20 mA) 10 k $\Omega$ -100 k $\Omega$ (I <sub>max</sub> = 6 mA)	1,5.10 <sup>-4</sup> .R		R = Measured Value

TSE ANKARA LABORATORIES  
CALIBRATION ACCREDITATION SCOPE

MEASURAND /DEVICE	MEASURING RANGE	CONDITIONS	MEASUREMENT CAPABILITY / UNCERTAINTY	NOTES
<b>DC Resistance</b> <b>DC Resistance</b> <b>Ölçerler</b> Multimeter: Resistance Microohmmeter Insulation resistance Tester	$1\Omega \leq R < 11\Omega$	$1 \text{ mA} \leq I_{\text{max}} \leq 125 \text{ mA}$	$7,4 \cdot 10^{-4} + 8 \text{ m}\Omega$	With 5520A R = Measured Value
	$11\Omega \leq R < 33\Omega$	$1 \text{ mA} \leq I_{\text{max}} \leq 125 \text{ mA}$	$3,5 \cdot 10^{-4} + 12 \text{ m}\Omega$	
	$33\Omega \leq R < 110\Omega$	$1 \text{ mA} \leq I_{\text{max}} \leq 70 \text{ mA}$	$1,3 \cdot 10^{-4} + 15 \text{ m}\Omega$	
	$110\Omega \leq R < 330\Omega$	$1 \text{ mA} \leq I_{\text{max}} \leq 40 \text{ mA}$	$7,1 \cdot 10^{-5} + 20 \text{ m}\Omega$	
	$330\Omega \leq R \leq 1,1\text{k}\Omega$	$1 \text{ mA} \leq I_{\text{max}} \leq 18 \text{ mA}$	$4 \cdot 10^{-5} + 25 \text{ m}\Omega$	
	$1,1\text{k}\Omega < R \leq 3,3\text{k}\Omega$	$100 \mu\text{A} \leq I_{\text{max}} \leq 5 \text{ mA}$	$7,1 \cdot 10^{-5} + 200 \text{ m}\Omega$	
	$3,3\text{k}\Omega < R \leq 11\text{k}\Omega$	$100 \mu\text{A} \leq I_{\text{max}} \leq 1,8\text{mA}$	$3,4 \cdot 10^{-5} + 200 \text{ m}\Omega$	
	$11\text{k}\Omega < R \leq 33\text{k}\Omega$	$10 \mu\text{A} \leq I_{\text{max}} \leq 0,5 \text{ mA}$	$5,2 \cdot 10^{-5} + 1,2 \Omega$	
	$33\text{k}\Omega < R < 110\text{k}\Omega$	$10 \mu\text{A} \leq I_{\text{max}} \leq 0,18\text{mA}$	$6,2 \cdot 10^{-5} + 6,0 \Omega$	
	$110\text{k}\Omega \leq R < 330\text{k}\Omega$	$10 \mu\text{A} \leq I_{\text{max}} \leq 50 \mu\text{A}$	$5,8 \cdot 10^{-5} + 13 \Omega$	
	$330\text{k}\Omega \leq R \leq 1,1\text{M}\Omega$	$1 \mu\text{A} \leq I_{\text{max}} \leq 50 \mu\text{A}$	$4,2 \cdot 10^{-5} + 20 \Omega$	
	$1,1\text{M}\Omega < R < 3,3\text{M}\Omega$	$250 \text{ nA} \leq I_{\text{max}} \leq 5 \mu\text{A}$	$1,0 \cdot 10^{-4} + 200 \Omega$	
	$3,3\text{M}\Omega < R \leq 11\text{M}\Omega$	$25 \text{ nA} \leq I_{\text{max}} \leq 1,8 \mu\text{A}$	$1,3 \cdot 10^{-4} + 550 \Omega$	
	$11\text{M}\Omega < R \leq 33\text{M}\Omega$	$25 \text{ nA} \leq I_{\text{max}} \leq 500 \text{ nA}$	$3,0 \cdot 10^{-4} + 4,2 \text{ k}\Omega$	
	$33\text{M}\Omega < R \leq 110\text{M}\Omega$	$2,5 \text{ nA} \leq I_{\text{max}} \leq 50 \text{ nA}$	$5,0 \cdot 10^{-4} + 21 \text{ k}\Omega$	
	$110 \text{ M}\Omega \leq R < 330\text{M}\Omega$	$2,5 \text{ nA} \leq I_{\text{max}} \leq 50 \text{ nA}$	$3,5 \cdot 10^{-3} \cdot R$	
	$330\text{M}\Omega \leq R \leq 1100\text{M}\Omega$	$1,0 \text{ nA} \leq I_{\text{max}} \leq 13 \text{ nA}$	$1,5 \cdot 10^{-2} \cdot R$	
				$2 \cdot 10^{-4} \cdot R$
				$4 \cdot 10^{-5} \cdot R$
				$2 \cdot 10^{-5} \cdot R$
				$2 \cdot 10^{-5} \cdot R$
				$2 \cdot 10^{-5} \cdot R$
				$3 \cdot 10^{-5} \cdot R$
			$5 \cdot 10^{-5} \cdot R$	
			$6 \cdot 10^{-5} \cdot R$	
			$7 \cdot 10^{-3} \cdot R$	
			$1,5 \cdot 10^{-2} \cdot R$	
			$2,5 \cdot 10^{-2} \cdot R$	
				R = Ölçülen Measured Value (With 5700A )
				R = Measured Value (With Calibrated Resistance Set)

TSE ANKARA LABORATORIES  
CALIBRATION ACCREDITATION SCOPE

MEASURAND/DEVICE	MEASURING RANGE	CONDITIONS	MEASUREMENT CAPABILITY / UNCERTAINTY	NOTES
<b>DC Resistance Sources and Standards</b> DC Resistance Standard Calibrator DC Current Shunt Resistance Boxes	$100 \mu\Omega \leq R < 10 \text{ m}\Omega$	100 $\mu\text{A}$ 20 A 1 mA 5,10,15,20 A 10 mA 5,10,15,20 A	$5,5 \cdot 10^{-5}R$	R=Measure Value  Comparision with reference resistors
DC Resistance Standard Calibrator Resistance DC Current Shunt Resistance Box	$10 \text{ m}\Omega \leq R < 100 \text{ m}\Omega$	10 mA 5,10,15,20 A  $I_{\max} = 1 \text{ A} (R_s = 100 \text{ m})$	$5,5 \cdot 10^{-5} R$	
DC Resistance Standard Calibrator Resistance DC Current Shunt Resistance Box	$100 \text{ m}\Omega \leq R < 1 \Omega$	$I_{\max} = 1 \text{ A} (R_s = 100 \text{ m})$ $I_{\max} = 320 \text{ mA} (R_s = 1)$	$1 \cdot 10^{-5} R$	

TSE ANKARA LABORATORIES  
CALIBRATION ACCREDITATION SCOPE

MEASURAND/ DEVICE	MEASURING RANGE	CONDITIONS	MEASUREMENT CAPABILITY / UNCERTAINTY	NOTES
DC Resistance Standard Calibrator Resistance DC Current Shunt Resistance Box	$1 \Omega \leq R < 100\Omega$	$I_{\max} = 320 \text{ mA}$ ( $R_s=1\Omega$ ) $I_{\max} = 100 \text{ mA}$ ( $R_s=10\Omega$ ) $I_{\max} = 32 \text{ mA}$ ( $R_s=100\Omega$ )	$7 \cdot 10^{-6} \cdot R$	R=Measure Value  Comparision with reference resistors
	$100\Omega \leq R < 10 \text{ k}\Omega$	$I_{\max} = 32 \text{ mA}$ ( $R_s=100\Omega$ ) $I_{\max} = 10 \text{ mA}$ ( $R_s=1\text{k}\Omega$ ) $I_{\max}=3,2\text{mA}$ ( $R_s=10\text{k}\Omega$ )	$5 \cdot 10^{-6} \cdot R$	
	$10 \text{ k}\Omega \leq R \leq 100 \text{ k}\Omega$	$I_{\max} = 3,2 \text{ mA}$ ( $R_s=10\text{k}\Omega$ ) $V_{\max}= 100 \text{ V}$ ( $R_s=100\text{k}\Omega$ )	$5 \cdot 10^{-6} \cdot R$	
	$100 \text{ k}\Omega < R \leq 10 \text{ M}\Omega$	$V_{\max}=100\text{V}$ ( $R_s=100\text{k}\Omega$ ) $V_{\max}=320\text{V}$ ( $R_s=1\text{M}\Omega$ )	$1,5 \cdot 10^{-5} R$	
	$10\text{M}\Omega < R \leq 100 \text{ M}\Omega$	$V_{\max}=320 \text{ V}$ ( $R_s=1\text{M}\Omega$ ) $V_{\max}=1000\text{V}$ ( $R_s=10\text{M}\Omega$ ) $V_{\max}=1000\text{V}$ ( $R_s=100\text{M}\Omega$ )	$2,0 \cdot 10^{-5} R$	

TSE ANKARA LABORATORIES  
CALIBRATION ACCREDITATION SCOPE

MEASURAND /DEVICE	MEASURING RANGE	CONDITIONS	MEASUREMENT CAPABILITY / UNCERTAINTY	NOTES
<b>AC Current (&lt;20 A)</b> <b>AC Current Measuring Devices</b> <b>Ölçerler</b> Multimeter: AC Current AC Clampmeter	100 µA ≤ I < 220 µA	10 Hz ≤ f < 10 kHz	1·10 <sup>-3</sup> ·I	I = Measured Value With 5700A
	1 mA ≤ I < 2,2 mA	10 Hz ≤ f < 20 Hz	8.10 <sup>-4</sup> ·I	
		20 Hz ≤ f < 40 Hz	4.10 <sup>-4</sup> ·I	
		40 Hz ≤ f < 1 kHz	9.10 <sup>-5</sup> ·I + 0,2 µA	
		1 kHz ≤ f < 5 kHz	8 ·10 <sup>-4</sup> ·I + 1 µA	
		5 kHz ≤ f ≤ 10 kHz	2 ·10 <sup>-3</sup> ·I + 2,5 µA	
	2,2 mA ≤ I < 22 mA	10 Hz ≤ f < 20 Hz	8.10 <sup>-4</sup> ·I + 2µA	
		20 Hz ≤ f < 40 Hz	4 ·10 <sup>-4</sup> ·I + 1,5 µA	
		40 Hz ≤ f < 1 kHz	2.10 <sup>-4</sup> ·I + 0,8 µA	
		1 kHz ≤ f < 5 kHz	8.10 <sup>-4</sup> ·I + 5,5 µA	
		5 kHz ≤ f ≤ 10 kHz	2.10 <sup>-3</sup> ·I + 13 µA	
	22 mA ≤ I < 220 mA	10 Hz ≤ f < 20 Hz	7,5 ·10 <sup>-4</sup> ·I + 20 µA	
		20 Hz ≤ f < 40 Hz	4.10 <sup>-4</sup> ·I + 13 µA	
		40 Hz ≤ f < 1 kHz	2.10 <sup>-4</sup> ·I + 8 µA	
		1 kHz ≤ f < 5 kHz	8.10 <sup>-4</sup> ·I + 55 µA	
		5 kHz ≤ f ≤ 10 kHz	2,5 ·10 <sup>-3</sup> ·I + 120 µA	
	220 mA ≤ I < 2,2 A	20 Hz ≤ f < 1 kHz	7.10 <sup>-4</sup> ·I + 190 µA	
		1 kHz ≤ f < 5 kHz	8,5.10 <sup>-4</sup> ·I + 270 µA	
		5 kHz ≤ f ≤ 10 kHz	9.10 <sup>-3</sup> ·I + 2,1 mA	
	2,2 A ≤ I < 3 A	45 Hz ≤ f < 1 kHz	5,1·10 <sup>-4</sup> ·I	
1 kHz ≤ f < 5 kHz		1,4·10 <sup>-3</sup> ·I		
2,2 A ≤ I < 3 A	5 kHz ≤ f < 10 kHz	2,2·10 <sup>-2</sup> ·I		
	45 Hz ≤ f < 100 Hz	6,3·10 <sup>-4</sup> ·I + 4 mA		
2,2 A ≤ I < 3 A	100 Hz ≤ f < 1 kHz	1,0·10 <sup>-3</sup> ·I + 4 mA	I = Measured Value With 5520A	
		1 kHz ≤ f < 5 kHz		2,5·10 <sup>-2</sup> ·I + 75 mA
3 A ≤ I < 11 A	45 Hz ≤ f < 100 Hz	1,2·10 <sup>-3</sup> ·I+ 15 mA		
	100 Hz ≤ f < 1 kHz	1,4·10 <sup>-3</sup> ·I+ 20 mA		
3 A ≤ I < 11 A	1 kHz ≤ f < 5 kHz	2,4·10 <sup>-3</sup> ·I+ 30 mA		
11 A ≤ I ≤ 20,5 A	30 Hz ≤ f < 1kHz	1.10 <sup>-3</sup> ·I+ 3 mA		
		1 kHz ≤ f ≤ 5 kHz		3.10 <sup>-3</sup> ·I+ 15 mA
11 A ≤ I ≤ 20,5 A	10,40,500,1k,5kHz	5.10 <sup>-4</sup> ·I		
11 A ≤ I ≤ 20,5 A			I=Ölçülen Değer 5700A+5220A	

TSE ANKARA LABORATORIES  
CALIBRATION ACCREDITATION SCOPE

MEASURAND /DEVICE	MEASURING RANGE	CONDITIONS	MEASUREMENT CAPABILITY / UNCERTAINTY	NOTES
	$1 \text{ A} \leq I \leq 20 \text{ A}$			With Y5020 Current Shunt
Multimeter: AC Current AC Clampmeter	$10 \text{ A} \leq I \leq 1025 \text{ A}$ $10 \text{ A} \leq I < 16,5 \text{ A}$ $16,5 \text{ A} \leq I \leq 1025 \text{ A}$	$45 \text{ Hz} \leq f \leq 65 \text{ Hz}$ $65 \text{ Hz} \leq f \leq 440 \text{ Hz}$ $65 \text{ Hz} \leq f \leq 440 \text{ Hz}$	$6 \cdot 10^{-3} \cdot I$ $1,3 \cdot 10^{-2} \cdot I$ $1 \cdot 10^{-2} \cdot I$	Clampmeter Calibration (With 5520A+50 Turn Coil )
<b>AC Current (&lt; 20 A)</b> <b>AC Current Sources</b> AC Current Source Calibrator: AC Current Transconductance Amplifier	$100 \mu\text{A} \leq I < 1 \text{ mA}$	$45 \text{ Hz} \leq f < 1\text{kHz}$	$1,1 \cdot 10^{-3} \cdot I + 450 \text{ nA}$	$I$ =Measured Value With 3458A
	$1\text{mA} \leq I < 10 \text{ mA}$	$45 \text{ Hz} \leq f < 100 \text{ Hz}$	$1 \cdot 10^{-3} \cdot I + 3,5\mu\text{A}$	
		$100 \text{ Hz} \leq f < 5\text{ k Hz}$	$7 \cdot 10^{-4} \cdot I + 3\mu\text{A}$	
		$5 \text{ kHz} \leq f \leq 20 \text{ kHz}$	$1 \cdot 10^{-3} \cdot I + 4\mu\text{A}$	
	$10\text{mA} \leq I < 100 \text{ mA}$	$45 \text{ Hz} \leq f < 100 \text{ Hz}$	$9 \cdot 10^{-4} \cdot I + 30\mu\text{A}$	
		$100 \text{ Hz} \leq f < 5\text{ k Hz}$	$6 \cdot 10^{-4} \cdot I + 25\mu\text{A}$	
		$5 \text{ kHz} \leq f \leq 20 \text{ kHz}$	$9 \cdot 10^{-4} \cdot I + 30\mu\text{A}$	
	$100\text{mA} \leq I < 1\text{A}$	$45 \text{ Hz} \leq f < 100 \text{ Hz}$	$1,1 \cdot 10^{-3} \cdot I + 300\mu\text{A}$	
		$100 \text{ Hz} \leq f < 5\text{ k Hz}$	$1,4 \cdot 10^{-3} \cdot I + 310\mu\text{A}$	
		$5 \text{ kHz} \leq f \leq 20 \text{ kHz}$	$3,5 \cdot 10^{-3} \cdot I + 510\mu\text{A}$	
$1 \text{ A} \leq I < 3 \text{ A}$	$10 \text{ Hz} \leq f < 5\text{ k Hz}$	$3,5 \cdot 10^{-3} \cdot I$	With Fluke 8846A	
$1 \text{ A} \leq I < 10 \text{ A}$	$10 \text{ Hz} \leq f \leq 5\text{ k Hz}$	$3,3 \cdot 10^{-3} \cdot I + 15 \text{ mA}$		
$1 \text{ A} \leq I \leq 20 \text{ A}$	10,40,500,1k,5kHz	$5 \cdot 10^{-4} \cdot I$	With Y5020 Current Shunt	
$10 \text{ A} \leq I < 16,5 \text{ A}$ $16,5 \text{ A} \leq I < 150 \text{ A}$ $150 \text{ A} \leq I \leq 1000 \text{ A}$	$10 \text{ Hz} \leq f < 100 \text{ Hz}$	$8,1 \cdot 10^{-2} \cdot I$	With Fluke 376 Clampmeter	
		$2,7 \cdot 10^{-2} \cdot I + 1 \text{ A}$		
		$2,7 \cdot 10^{-2} \cdot I$		
$10 \text{ A} \leq I < 16,5 \text{ A}$ $16,5 \text{ A} \leq I < 150 \text{ A}$ $150 \text{ A} \leq I \leq 1000 \text{ A}$	$100 \text{ Hz} \leq f \leq 500 \text{ Hz}$	$8,7 \cdot 10^{-2} \cdot I$		
		$3,3 \cdot 10^{-2} \cdot I + 1,1 \text{ A}$		
		$3,3 \cdot 10^{-2} \cdot I$		



TSE ANKARA LABORATORIES  
CALIBRATION ACCREDITATION SCOPE

MEASURAND /DEVICE	MEASURING RANGE	CONDITIONS	MEASUREMENT CAPABILITY / UNCERTAINTY	NOTES
<b>AC Voltage (&lt; 1100 V)</b> <b>AC Voltage Measuring Device</b> Multimeter: AC Voltage AC Measuring Standard AC Voltmeter	$2 \text{ mV} \leq U < 2,2 \text{ mV}$	$10 \text{ Hz} \leq f < 20 \text{ Hz}$ $20 \text{ Hz} \leq f < 40 \text{ Hz}$ $40 \text{ Hz} \leq f < 20 \text{ kHz}$ $20 \text{ kHz} \leq f < 50 \text{ kHz}$ $50 \text{ kHz} \leq f < 100 \text{ kHz}$ $100 \text{ kHz} \leq f < 300 \text{ kHz}$ $300 \text{ kHz} \leq f < 500 \text{ kHz}$ $500 \text{ kHz} \leq f < 1 \text{ MHz}$	$3 \cdot 10^{-3} \cdot U + 6 \mu\text{V}$ $2,5 \cdot 10^{-3} \cdot U + 5 \mu\text{V}$ $2,5 \cdot 10^{-3} \cdot U + 5 \mu\text{V}$ $2,5 \cdot 10^{-3} \cdot U + 6 \mu\text{V}$ $4,2 \cdot 10^{-3} \cdot U + 8 \mu\text{V}$ $7,5 \cdot 10^{-3} \cdot U + 15 \mu\text{V}$ $4,5 \cdot 10^{-3} \cdot U + 8 \mu\text{V}$ $1,5 \cdot 10^{-2} \cdot U + 30 \mu\text{V}$ $1,5 \cdot 10^{-2} \cdot U + 30 \mu\text{V}$	U= Measured Value With 5700A
	$2,2 \text{ mV} \leq U < 22 \text{ mV}$	$10 \text{ Hz} \leq f < 20 \text{ Hz}$ $20 \text{ Hz} \leq f < 40 \text{ Hz}$ $40 \text{ Hz} \leq f < 20 \text{ kHz}$ $20 \text{ kHz} \leq f < 50 \text{ kHz}$ $50 \text{ kHz} \leq f < 100 \text{ kHz}$ $100 \text{ kHz} \leq f < 300 \text{ kHz}$ $300 \text{ kHz} \leq f < 500 \text{ kHz}$ $500 \text{ kHz} \leq f < 1 \text{ MHz}$	$9 \cdot 10^{-4} \cdot U + 6 \mu\text{V}$ $5 \cdot 10^{-4} \cdot U + 6 \mu\text{V}$ $4 \cdot 10^{-4} \cdot U + 6 \mu\text{V}$ $7 \cdot 10^{-4} \cdot U + 6 \mu\text{V}$ $1,2 \cdot 10^{-3} \cdot U + 9 \mu\text{V}$ $2,0 \cdot 10^{-3} \cdot U + 15 \mu\text{V}$ $3,0 \cdot 10^{-3} \cdot U + 30 \mu\text{V}$ $3,0 \cdot 10^{-3} \cdot U + 30 \mu\text{V}$  $7 \cdot 10^{-4} \cdot U + 26 \mu\text{V}$ $2,5 \cdot 10^{-4} \cdot U + 6 \mu\text{V}$ $1,5 \cdot 10^{-4} \cdot U + 8 \mu\text{V}$ $4 \cdot 10^{-4} \cdot U + 15 \mu\text{V}$ $9 \cdot 10^{-4} \cdot U + 30 \mu\text{V}$	
	$22 \text{ mV} \leq U < 220 \text{ mV}$	$10 \text{ Hz} \leq f < 20 \text{ Hz}$ $20 \text{ Hz} \leq f < 40 \text{ Hz}$ $40 \text{ Hz} \leq f < 20 \text{ kHz}$ $20 \text{ kHz} \leq f < 50 \text{ kHz}$ $50 \text{ kHz} \leq f < 100 \text{ kHz}$ $100 \text{ kHz} \leq f < 300 \text{ kHz}$ $300 \text{ kHz} \leq f < 500 \text{ kHz}$ $500 \text{ kHz} \leq f < 1 \text{ MHz}$	$1,2 \cdot 10^{-3} \cdot U + 36 \mu\text{V}$ $2 \cdot 10^{-3} \cdot U + 65 \mu\text{V}$ $4 \cdot 10^{-3} \cdot U + 100 \mu\text{V}$  $6 \cdot 10^{-4} \cdot U + 200 \mu\text{V}$ $3 \cdot 10^{-4} \cdot U + 65 \mu\text{V}$ $9 \cdot 10^{-5} \cdot U + 25 \mu\text{V}$ $1,5 \cdot 10^{-4} \cdot U + 45 \mu\text{V}$ $5 \cdot 10^{-4} \cdot U + 250 \mu\text{V}$	
	$220 \text{ mV} \leq U < 2,2 \text{ V}$	$10 \text{ Hz} \leq f < 20 \text{ Hz}$ $20 \text{ Hz} \leq f < 40 \text{ Hz}$ $40 \text{ Hz} \leq f < 20 \text{ kHz}$	$1,2 \cdot 10^{-3} \cdot U + 600 \mu\text{V}$ $2,6 \cdot 10^{-3} \cdot U + 1,3 \text{ mV}$	

MEASURAND /DEVICE	MEASURING RANGE	CONDITIONS	MEASUREMENT CAPABILITY / UNCERTAINTY	NOTES
		$20 \text{ kHz} \leq f < 50 \text{ kHz}$ $50 \text{ kHz} \leq f < 100 \text{ kHz}$ $100 \text{ kHz} \leq f < 300 \text{ kHz}$ $300 \text{ kHz} \leq f < 500 \text{ kHz}$ $500 \text{ kHz} \leq f < 1 \text{ MHz}$		
<b>AC Voltage (&lt; 1100 V)</b> <b>AC Voltage Measuring Device</b> Multimeter: AC Voltage AC Measuring Standard AC Voltmeter	$2,2 \text{ V} \leq U < 22 \text{ V}$  $22 \text{ V} \leq U < 220 \text{ V}$  $220 \text{ V} \leq U \leq 1000 \text{ V}$	$10 \text{ Hz} \leq f < 20 \text{ Hz}$ $20 \text{ Hz} \leq f < 40 \text{ Hz}$ $40 \text{ Hz} \leq f < 20 \text{ kHz}$ $20 \text{ kHz} \leq f \leq 50 \text{ kHz}$ $50 \text{ kHz} \leq f < 100 \text{ kHz}$ $100 \text{ kHz} \leq f < 300 \text{ kHz}$ $300 \text{ kHz} \leq f < 500 \text{ kHz}$ $500 \text{ kHz} \leq f < 1 \text{ MHz}$  $10 \text{ Hz} \leq f < 20 \text{ Hz}$ $20 \text{ Hz} \leq f < 40 \text{ Hz}$ $40 \text{ Hz} \leq f < 20 \text{ kHz}$ $20 \text{ kHz} \leq f \leq 50 \text{ kHz}$ $50 \text{ kHz} \leq f < 100 \text{ kHz}$  $15 \text{ Hz} \leq f < 50 \text{ Hz}$ $50 \text{ Hz} \leq f \leq 1 \text{ kHz}$	$5 \cdot 10^{-4} \cdot U + 2 \text{ mV}$ $2 \cdot 10^{-4} \cdot U + 650 \mu\text{V}$ $9 \cdot 10^{-5} \cdot U + 230 \mu\text{V}$ $1,5 \cdot 10^{-4} \cdot U + 440 \mu\text{V}$ $1,5 \cdot 10^{-4} \cdot U + 45 \mu\text{V}$ $3 \cdot 10^{-4} \cdot U + 90 \mu\text{V}$ $6 \cdot 10^{-3} \cdot U + 2,6 \text{ mV}$ $3,1 \cdot 10^{-3} \cdot U + 7,5 \text{ mV}$  $6 \cdot 10^{-4} \cdot U + 20 \text{ mV}$ $2 \cdot 10^{-4} \cdot U + 7 \text{ mV}$ $9 \cdot 10^{-5} \cdot U + 3 \text{ mV}$ $2,5 \cdot 10^{-4} \cdot U + 9 \text{ mV}$ $5,5 \cdot 10^{-4} \cdot U + 20$ $4,5 \cdot 10^{-4} \cdot U + 110 \text{ mV}$ $9 \cdot 10^{-5} \cdot U + 25 \text{ mV}$	U= Measured Value With 5700A
<b>DC Power</b> <b>DC Powermeters</b> DC Watmeters	$0,1 \text{ W} \leq P < 10 \text{ kW}$  $10 \text{ kW} \leq P \leq 20 \text{ kW}$	$100 \text{ mA} - 10 \text{ A}$ $1 \text{ V} - 1000 \text{ V}$  $10 \text{ A} - 20 \text{ A}$ $1 \text{ V} - 1000 \text{ V}$	$6,5 \cdot 10^{-4} \cdot P$  $8,5 \cdot 10^{-4} \cdot P$	P= Measured Value With 5520A
<b>AC Power and Energy:</b> Active Power: Mono Phase Powermeter, Wattmeter	$0,1 \text{ W} \leq P \leq 10 \text{ kW}$  $10 \text{ kW} \leq P \leq 20 \text{ kW}$	$0,1 \text{ A} \leq I < 10 \text{ A}$ $1 \text{ V} \leq V < 1000 \text{ V}$ $10 \text{ Hz} \leq f \leq 1 \text{ kHz}$  $10 \text{ A} \leq I < 20 \text{ A}$ $500 \text{ V} \leq V < 1000 \text{ V}$ $10 \text{ Hz} \leq f \leq 1 \text{ kHz}$	$1,5 \cdot 10^{-3} \cdot P$  $2,5 \cdot 10^{-3} \cdot P$	P= Measured Value With 5520A

MEASURAND /DEVICE	MEASURING RANGE	CONDITIONS	MEASUREMENT CAPABILITY / UNCERTAINTY	NOTES
<b>AC Voltage (&lt; 1100 V)</b> <b>AC Voltage Sources</b> AC Voltage Sources AC Kalibrator	$2 \text{ mV} \leq U < 10 \text{ mV}$	$40 \text{ Hz} \leq f < 1 \text{ kHz}$ $1 \text{ kHz} \leq f < 20 \text{ kHz}$	$4 \cdot 10^{-4} \cdot U + 2 \text{ } \mu\text{V}$ $5 \cdot 10^{-4} \cdot U + 2 \text{ } \mu\text{V}$	U=Measured Value With 3458A
	$10 \text{ mV} \leq U < 100 \text{ mV}$	$1 \text{ Hz} \leq f < 40 \text{ Hz}$	$1,3 \cdot 10^{-4} \cdot U + 6 \text{ } \mu\text{V}$	
		$40 \text{ Hz} \leq f < 1 \text{ kHz}$	$1,1 \cdot 10^{-4} \cdot U + 4 \text{ } \mu\text{V}$	
		$1 \text{ kHz} \leq f < 20 \text{ kHz}$	$2,1 \cdot 10^{-4} \cdot U$	
		$20 \text{ kHz} \leq f \leq 50 \text{ kHz}$	$4 \cdot 10^{-4} \cdot U + 6 \text{ } \mu\text{V}$	
		$50 \text{ kHz} < f \leq 100 \text{ kHz}$	$1,1 \cdot 10^{-3} \cdot U + 21 \text{ } \mu\text{V}$	
		$1 \text{ Hz} \leq f < 40 \text{ Hz}$	$1,4 \cdot 10^{-4} \cdot U + 60 \text{ } \mu\text{V}$	
	$100 \text{ mV} \leq U < 1 \text{ V}$	$40 \text{ Hz} \leq f < 1 \text{ kHz}$	$1,2 \cdot 10^{-4} \cdot U + 35 \text{ } \mu\text{V}$	
		$1 \text{ kHz} \leq f < 20 \text{ kHz}$	$2 \cdot 10^{-4} \cdot U + 45 \text{ } \mu\text{V}$	
		$20 \text{ kHz} \leq f \leq 50 \text{ kHz}$	$4 \cdot 10^{-4} \cdot U + 60 \text{ } \mu\text{V}$	
		$50 \text{ kHz} \leq f < 100 \text{ kHz}$	$1,1 \cdot 10^{-3} \cdot U + 210 \text{ } \mu\text{V}$	
		$100 \text{ kHz} \leq f < 300 \text{ kHz}$	$\mu\text{V } \mu\text{V}$	
		$300 \text{ kHz} \leq f < 1 \text{ MHz}$	$3,6 \cdot 10^{-3} \cdot U + 470 \text{ } \mu\text{V}$	
	$1 \text{ V} \leq U < 10 \text{ V}$	$1 \text{ Hz} \leq f < 40 \text{ Hz}$	$\mu\text{V}$	
		$40 \text{ Hz} \leq f < 1 \text{ kHz}$	$1,2 \cdot 10^{-2} \cdot U + 1,5 \text{ mV}$	
		$1 \text{ kHz} \leq f < 20 \text{ kHz}$	$1,3 \cdot 10^{-4} \cdot U + 600 \text{ } \mu\text{V}$	
$20 \text{ kHz} \leq f \leq 50 \text{ kHz}$		$1,4 \cdot 10^{-4} \cdot U + 350 \text{ } \mu\text{V}$		
$50 \text{ kHz} \leq f < 100 \text{ kHz}$		$2,2 \cdot 10^{-4} \cdot U + 650 \text{ } \mu\text{V}$		
$100 \text{ kHz} \leq f < 300 \text{ kHz}$		$4,0 \cdot 10^{-4} \cdot U + 850 \text{ } \mu\text{V}$		
$10 \text{ V} \leq U < 100 \text{ V}$	$1 \text{ kHz} \leq f < 20 \text{ kHz}$	$1,2 \cdot 10^{-3} \cdot U + 3,5 \text{ mV}$		
	$20 \text{ kHz} \leq f < 100 \text{ kHz}$	$3,8 \cdot 10^{-3} \cdot U + 6 \text{ mV}$		
	$1 \text{ Hz} \leq f < 40 \text{ Hz}$	$1,2 \cdot 10^{-2} \cdot U + 15 \text{ mV}$		
	$40 \text{ Hz} \leq f < 1 \text{ kHz}$			
	$1 \text{ kHz} \leq f < 20 \text{ kHz}$	$2,7 \cdot 10^{-4} \cdot U + 7 \text{ mV}$		
	$20 \text{ kHz} \leq f \leq 50 \text{ kHz}$	$2,7 \cdot 10^{-4} \cdot U + 5 \text{ mV}$		
$100 \text{ V} \leq U \leq 1000 \text{ V}$	$50 \text{ kHz} \leq f < 100 \text{ kHz}$	$5 \text{ mV}$		
	$1 \text{ Hz} \leq f \leq 40 \text{ Hz}$	$2,7 \cdot 10^{-4} \cdot U + 5 \text{ mV}$		
	$40 \text{ Hz} \leq f < 1 \text{ kHz}$	$4,5 \cdot 10^{-4} \cdot U + 7 \text{ mV}$		
	$1 \text{ kHz} \leq f < 20 \text{ kHz}$	$1,5 \cdot 10^{-2} \cdot U + 170 \text{ mV}$		
	$20 \text{ kHz} \leq f < 50 \text{ kHz}$	$\text{mV}$		
		$5,5 \cdot 10^{-4} \cdot U + 100 \text{ mV}$		
	$1,1 \cdot 10^{-4} \cdot U + 40 \text{ mV}$			
	$1,9 \cdot 10^{-4} \cdot U + 40 \text{ mV}$			

MEASURAND /DEVICE	MEASURING RANGE	CONDITIONS	MEASUREMENT CAPABILITY / UNCERTAINTY	NOTES	
<b>Capacitance</b> Capacitance Measuring Devices LCR Meter:	1 nF	f = 1 kHz	$1.8 \cdot 10^{-4} \cdot C$	C = Measured Value	
	10 nF		$1.8 \cdot 10^{-4} \cdot C$		
	100 nF		$1.8 \cdot 10^{-4} \cdot C$		
	1 $\mu$ F		$1.8 \cdot 10^{-4} \cdot C$		
		10 Hz- 10 kHz			C = Measured Value With Fluke 5520A
	$0.22 \leq C < 0.3999$	10 Hz- 10 kHz	% 5.0		
	nF	10 Hz- 3000 Hz	% 2.5		
	$0.4 \leq C < 1.0999$ nF	10 Hz- 1000 Hz	% 1.3		
	$1.1 \leq C < 3.2999$ nF	10 Hz- 1000 Hz	% 0.6		
	$3.3 \leq C < 10.9999$ nF	10 Hz- 1000 Hz	% 1.0		
	$11 \leq C < 32.999$ nF	10 Hz- 600 Hz	% 0.5		
	$33 \leq C < 109.999$ nF	10 Hz- 300 Hz	% 0.5		
	nF	10 Hz- 150 Hz	% 0.5		
	$110 \leq C < 329.999$ nF	10 Hz- 120 Hz	% 0.5		
	nF	10 Hz- 80 Hz	% 0.6		
	$0.33 \leq C < 1.09999$ $\mu$ F		% 0.6		
$1.1 \leq C < 3.29999$ $\mu$ F					
$3.3 \leq C < 10.9999$ $\mu$ F					
$11 \leq C < 32.999$ $\mu$ F					
$33 \leq C < 109.999$ $\mu$ F					

MEASURAND /DEVICE	MEASURING RANGE	CONDITIONS	MEASUREMENT CAPABILITY / UNCERTAINTY	NOTES
<b>Inductance L</b> Inductance Measuring Device LCR Meter	100 $\mu$ H	100 Hz	$1,2 \cdot 10^{-3} \cdot L$	L =Measured Value
		200 Hz	$4 \cdot 10^{-4} \cdot L$	
		400 Hz	$4 \cdot 10^{-4} \cdot L$	
		1 kHz	$4 \cdot 10^{-4} \cdot L$	
		10 kHz	$5 \cdot 10^{-4} \cdot L$	
	1 mH	100 Hz	$3,5 \cdot 10^{-4} \cdot L$	
		200 Hz	$3 \cdot 10^{-4} \cdot L$	
		400 Hz	$3 \cdot 10^{-4} \cdot L$	
		1 kHz	$3 \cdot 10^{-4} \cdot L$	
		10 kHz	$3,5 \cdot 10^{-4} \cdot L$	
	10 mH	100 Hz	$3 \cdot 10^{-4} \cdot L$	
		200 Hz	$3 \cdot 10^{-4} \cdot L$	
		400 Hz	$3 \cdot 10^{-4} \cdot L$	
		1 kHz	$3 \cdot 10^{-4} \cdot L$	
		10 kHz	$4 \cdot 10^{-4} \cdot L$	
	100 mH	100 Hz	$3 \cdot 10^{-4} \cdot L$	
		200 Hz	$3 \cdot 10^{-4} \cdot L$	
		400 Hz	$3 \cdot 10^{-4} \cdot L$	
		1 kHz	$3 \cdot 10^{-4} \cdot L$	
		4 kHz	$3 \cdot 10^{-4} \cdot L$	
1 H	10 kHz	$3,5 \cdot 10^{-4} \cdot L$		
	100 Hz	$3 \cdot 10^{-4} \cdot L$		
	200 Hz	$3 \cdot 10^{-4} \cdot L$		
	400 Hz	$3 \cdot 10^{-4} \cdot L$		
	1 kHz	$3 \cdot 10^{-4} \cdot L$		

MEASURAND/D EVICE	MEASURING RANGE	CONDITIONS	MEASUREMENT CAPABILITY / UNCERTAINTY	NOTES
<b>Time and Frequency</b> <b>Frequency</b> <b>Frequency Sources</b> Frequency Source	$1 \text{ Hz} \leq f \leq 10 \text{ Hz}$ $10 \text{ Hz} \leq f < 100 \text{ Hz}$ $100 \text{ Hz} \leq f < 1 \text{ kHz}$ $1 \text{ kHz} \leq f < 10 \text{ kHz}$ $10 \text{ kHz} \leq f < 100 \text{ kHz}$ $100 \text{ kHz} \leq f < 230$ MHz $230 \text{ MHz} \leq f \leq 40$ GHz	Gate Time 10 s  Amplitude $\leq 5V_{\text{rms}}$	$5 \cdot 10^{-6} \cdot f$ $1 \cdot 10^{-6} \cdot f$ $1 \cdot 10^{-7} \cdot f$ $1 \cdot 10^{-8} \cdot f$ $1 \cdot 10^{-9} \cdot f$ $2 \cdot 10^{-10} \cdot f$  $5 \cdot 10^{-11} \cdot f$	$f$ : Measured Frequency [Hz]  With Counter Synchronized via rubidium oscillator
<b>Time and Frequency</b> <b>Frequency</b> <b>Frequency Counters</b> Frequency Counter	$10 \text{ Hz} \leq f < 100 \text{ Hz}$ $100 \text{ Hz} \leq f < 1 \text{ kHz}$ $1 \text{ kHz} \leq f < 100 \text{ kHz}$ $100 \text{ kHz} \leq f \leq$ 40GHz	Gate Time 10 s  Amplitude $\leq 5 V_{\text{rms}}$	$1 \cdot 10^{-7} \cdot f$ $1 \cdot 10^{-8} \cdot f$ $1 \cdot 10^{-9} \cdot f$ $1 \cdot 10^{-10} \cdot f$	$f$ : Measured Frequency [Hz]  With Counter Synchronized via rubidium oscillator
<b>Time and Frequency</b> <b>Time Interval</b> Time Interval Measuring Devices	$100 \text{ ps} \leq t < 1 \mu\text{s}$ $1 \mu\text{s} \leq t < 100 \mu\text{s}$ $100 \mu\text{s} \leq t < 1 \text{ ms}$ $1 \text{ ms} \leq t < 10 \text{ ms}$ $10 \text{ ms} \leq t < 100 \text{ ms}$ $100 \text{ ms} \leq t < 1 \text{ s}$ $1 \text{ s} \leq t < 10 \text{ s}$ $10 \text{ s} \leq t < 100 \text{ s}$ $100 \text{ s} \leq t \leq 1000 \text{ s}$	Gate Time 10 s  Amplitude $\leq 5 V_{\text{rms}}$	$1 \cdot 10^{-10} \cdot t$ $1 \cdot 10^{-9} \cdot t$ $1 \cdot 10^{-8} \cdot t$ $1 \cdot 10^{-7} \cdot t$ $1 \cdot 10^{-6} \cdot t$ $1 \cdot 10^{-5} \cdot t$ $1 \cdot 10^{-4} \cdot t$ $1 \cdot 10^{-3} \cdot t$ $1 \cdot 10^{-2} \cdot t$	$t$ : Measured Time Interval [s]  With Counter Synchronized via rubidium oscillator

MEASURAND/DEVICE	MEASURING RANGE	CONDITIONS	MEASUREMENT CAPABILITY / UNCERTAINTY	NOTES
<b>Time and Frequency</b> <b>Time Interval</b> Stopwatches	$-30,00 \text{ s/day} \leq t \leq +30,00$ $\text{s/day } 1 \text{ s} \leq t \leq 3600 \text{ s}$		$0,04 \text{ s/g}$ 100 ms	<i>t</i> : Measured daily deviation [s/day] or time Interval [s] Direct reading via reference calibrator Comparison with reference frequency counter
<b>Time Frequency</b> <b>Frequency</b> <b>Frequency Counter</b> Optical Tachometers	$60 \text{ rpm} \leq \omega \leq 99999 \text{ rpm}$	$r = 0,001 \text{ rpm}$ $r = 0,01 \text{ rpm}$ $r = 0,1 \text{ rpm}$ $r = 1 \text{ rpm}$ $r = 10 \text{ rpm}$	$0,001 \text{ rpm}$ $0,006 \text{ rpm}$ $0,06 \text{ rpm}$ $0,6 \text{ rpm}$ $6 \text{ rpm}$	Measuring frequency using laser led $\omega$ : Measured Value [rpm] <i>r</i> : Resolution [rpm]

#### BALANCES

Nonautomatic Weighing Instruments	$m \leq 300 \text{ g}$ $m \leq 10 \text{ kg}$ $m \leq 5 \text{ kg}$ $m \leq 150 \text{ kg}$	With E2 Class Weights With F1 Class Weights With F2 Class Weights With M1 Class Weights	$2,0 \cdot 10^{-6}$ $6,2 \cdot 10^{-6}$ $2,0 \cdot 10^{-5}$ $8,5 \cdot 10^{-5}$	With procedure written according to Euromet Cg-18 v.04 guide <i>m</i> : balance capacity (Weight)
-----------------------------------	--	--	--	--

**MATERIAL TESTING MACHINES**

Concrete Test Hammer	10 N/mm <sup>2</sup> ≤ P ≤ 100 N/mm <sup>2</sup>	TS EN 12504-2	3%	With reference anvil
Fatigue Testing Machine Dynamic Calibration	Fatigue Testing Machine Dynamic Calibration	MIL STD 1312B ASTM E467 ISO 4965-2	% 0,32	With reference load cells
Tensile-Compression Bending-Spring Force Test and Concrete Test Machine Calibration	1N≤F≤1MN 1N≤F≤ 2MN 1mN≤F≤50N 1N≤F≤220N 1N≤F≤3MN	TS EN ISO 7500-1 ASTM E 4 TS EN 12390-4	% 0,16 % 0,16 % 0,10 % 0,10 % 0,32	Compression (With 0.5 Class Load Cell) Tensile (With 0.5 Class Load Cell) Tensile (With E2 class weights) Compression (With F1 Class Weight) Compression ((With 1 Class Load Cell )
<b>Mechanical Energy</b> Charpy Impact Testing Machine Calibration	Nominal Energy 0,5J ≤ A <sub>p</sub> ≤ 750J	TS EN ISO 148-2 ASTM E23 DIN 51222	Forcet: 0,12% Pendulum Length: 1mm Angle: 0,03° Time:0,04s	Measurement uncertainty is calculated for the following parameters. 1 - Resonance status. 2 - Potential Energy. 3 - Indicator deviation.
Uzunluk ölçer Extensometre	0 mm ≤ L ≤ 60 mm	TS EN ISO 9513	1,5 10 <sup>-3</sup> ×L Not lower than 0,5 μm	Measurment Method: Incremental



**HARDNESS**

MEASURAND /DEVICE	MEASURING RANGE	CONDITIONS	MEASUREMENT CAPABILITY / UNCERTAINTY	NOTES
Brinell Vickers  Rockwell  Hardness Measuring Devices	60HB≤HB≤450HB 200HV≤HV≤840HV  20 HRA ≤ HRA ≤ 65 HRA 66 HRA ≤ HRA ≤ 88 HRA  20 HRB ≤ HRB ≤ 55 HRB 56 HRB ≤ HRB ≤ 100 HRB  20 HRC ≤ HRC ≤ 55 HRC 56 HRC ≤ HRC ≤ 70 HRC  12 HRT ≤ HRT ≤ 93 HRT 20 HRN ≤ HRT ≤ 90 HRN	TS EN ISO 6506-2 TS EN ISO 6507-2 TS EN ISO 6508-2	2%HB 2%HV  1,0HRA  0,5HRA  1,5HRB  1,0HRB  1,0HRC  0,5HRC  2,0HRT  1,0HRN	These value are uncertainties obtained by undirect calibration with hardness blocks
Hardness measuring Devices Trace Depth Inspectetion	0mm ≤ L ≤ 10mm	TS EN ISO 6507-2 TS EN ISO 6506-2	1,5 10 <sup>-3</sup> ×L Lower than 0,5 μm	With object micrometer
Shoremeter	<i>Shore A</i> <i>Shore D</i>	Direct Calibration	1 Shore A 1 Shore D	ISO 18898 ASTM D2240

**TEMPERATURE**

MEASURAND /DEVICE	MEASURING RANGE	CONDITIONS	MEASUREMENT CAPABILITY / UNCERTAINTY	NOTES
Ice Point	0°C	Comparison Method	±0,030°C	Comparison of 2 thermometers
Resistance Thermometer	-70°C ≤ T < 5°C	Comparison method (Liquid Bath)	0,060 °C	t:Measured Temperature Including Ice point Uncertainty
	5°C ≤ T < 85°C		0,045 °C	
	85°C ≤ T ≤ 250°C		0,080 °C	
Liquid Glass Thermometers	-70°C ≤ T < 5°C	Comparison method (Liquid Bath)	0,060 °C	t:Measured Temperature Including Ice point Uncertainty
	5°C ≤ T < 85°C		0,045 °C	
	85°C ≤ T ≤ 250°C		0,080 °C	
Thermocouples	-70°C ≤ T < 5°C	Comparison method	0,060 °C	t:Measured Temperature With liquid bath and reference PRT
	5°C ≤ T < 85°C		0,045 °C	
	85°C ≤ T ≤ 250°C		0,080 °C	
	600°C ≤ T < 1100°C		2,5°C	
	1100°C ≤ T ≤ 1550°C		3,0°C	
Digital/Analog Thermometers	-70°C ≤ T < 5°C	Comparison method	0,060 °C	t:Measured Value including ice point uncertainty With liquid bath and reference PRT
	5°C ≤ T < 85°C		0,045 °C	
	85°C ≤ T ≤ 250°C		0,080 °C	
	600°C ≤ T < 1100°C		2,5°C	
	1100°C ≤ T ≤ 1550°C		3,0°C	

				With dry block calibrator and thermocouple
Detection of temperature distribution of the temperature controlled volume (sterilizer, incubator, oven, air conditioning cabinet, freezers, cold rooms, water baths etc.	$-70^{\circ}\text{C} \leq T \leq 100^{\circ}\text{C}$ $100^{\circ}\text{C} < T \leq 175^{\circ}\text{C}$ $\%20 \text{ rh} \leq \text{RH} \leq \%80 \text{ rh}$	At site calibration using mobile calibration system Distribution of temperature and humidity	$\pm 0,7^{\circ}\text{C}$ $\pm 1,0^{\circ}\text{C}$ $\%3,0 \text{ rh}$	With procedure written according to TS EN 60066-3-1 1, Ts EN 60068_3_5, EURAMET cg.20, DAkks DKD R_5-7 standarts
Ash Furnace	$250^{\circ}\text{C} \leq T < 550^{\circ}\text{C}$ $550^{\circ}\text{C} \leq T \leq 1200^{\circ}\text{C}$	Temperature distribution	$1,5^{\circ}\text{C}$ $3,5^{\circ}\text{C}$	t: Measured Value Temperature distribution Calibration both on site and in laboratory t: Measured value

**Torque**

<b>Toqrque Wrench</b>	<b><math>0,2 \text{ N}\cdot\text{m} \leq M \leq 1000 \text{ N}\cdot\text{m}</math></b>	<b>Temperature: 18 °C between 28°C Minimum distribution <math>\pm 1</math> °C RH &lt; 90 %</b>	<b>% 0,2</b>	<b>Procedurs written according to TS ISO 6789-1ve TS ISO 6789-2 standarts. Calibration for both directions</b>
-----------------------	--	--	--------------	--

## Akreditasyon Talep Edilen Kapsamlar (Sayfa 31/31)

### Dimension

Outside Micrometer	$L \leq 25 \text{ mm}$  $25 \text{ mm} < L \leq 300 \text{ mm}$  $300 \text{ mm} < L \leq 1000 \text{ mm}$	$r: 0,01 \text{ mm}$ $r: 0,001 \text{ mm}$ $r: 0,0001 \text{ mm}$  $r: 0,01 \text{ mm}$ $r: 0,001 \text{ mm}$  $r: 0,01 \text{ mm}$	$3,1 + 5 \cdot L) \mu\text{m}$ $( 1,4 + 9 \cdot L ) \mu\text{m}$ $( 1,2 + 11 \cdot L ) \mu\text{m}$  $( 3,1 + 26 \cdot L ) \mu\text{m}$ $( 1,4 + 30 \cdot L ) \mu\text{m}$  $( 3,1 + 31 \cdot L ) \mu\text{m}$	VDI/VDE/DGQ 2618 Part 10.1 L: Measured value (m) r: çresolution
Depth Micrometer	$L \leq 300 \text{ mm}$	$r: 0,01 \text{ mm}$	$( 3,1 + 25 \cdot L ) \mu\text{m}$	VDI/VDE/DGQ 2618 Part 10.5  <i>L: Measured Value(m)</i>  <i>r: Resolution</i>
Internal Micrometers with 2 Point Contact	$25 \text{ mm} \leq L \leq 40 \text{ mm}$	$r: 0,01 \text{ mm}$ $r: 0,001 \text{ mm}$	$( 14,2 + 5 \cdot L ) \mu\text{m}$ $( 11,6 + 6 \cdot L ) \mu\text{m}$	VDI/VDE/DGQ 2618 Part 10.7  <i>L: Measured Value(m)</i> <i>r: Resolution</i>
Internal Micrometers with 2 Point Contact	$5 \text{ mm} \leq L \leq 40 \text{ mm}$	$r: 0,01 \text{ mm}$ $r: 0,005 \text{ mm}$ $r: 0,001 \text{ mm}$	$( 14,2 + 5 \cdot L ) \mu\text{m}$ $( 12,3 + 6 \cdot L ) \mu\text{m}$ $( 11,6 + 6 \cdot L ) \mu\text{m}$	VDI/VDE/DGQ 2618 Part 10.8  L: Measured Value (m) r: Resolution

**Akreditasyon Talep Edilen Kapsamlar (Sayfa 31/31)**

Caliper	L ≤ 200 mm 200 mm < L ≤ 500 mm 500 mm < L ≤ 1000 mm	r: 0,01 mm r: 0,02 mm r: 0,05 mm r: 0,1 mm r: 0,01 mm r: 0,02 mm r: 0,05 mm r: 0,1 mm r: 0,01 mm r: 0,02 mm r: 0,05 mm r: 0,1 mm	( 10 + 11 · L ) μm ( 12,9 + 9 · L ) μm ( 29,4 + 4 · L ) μm ( 58 + 2 · L ) μm ( 10 + 21 · L ) μm ( 12,9 + 18 · L ) μm ( 29,4 + 10 · L ) μm ( 58 + 5 · L ) μm ( 10 + 27 · L ) μm ( 12,9 + 25 · L ) μm ( 29,5 + 17 · L ) μm ( 58 + 10 · L ) μm	VDI/VDE/DGQ 2618 Part 9.1 Outside diameter Inside diameter, depth, step, level Measurement L: Measured Value(m) r: Resolution
Depth Caliper	L ≤ 300 mm  300 mm < L ≤ 1000 mm	r: 0,01 mm r: 0,02 mm r: 0,05 mm r: 0,1 mm  r: 0,01 mm r: 0,02 mm r: 0,05 mm r: 0,1 mm	( 10 + 15 · L ) μm ( 13 + 13 · L ) μm ( 29,4 + 6 · L ) μm ( 58 + 3 · L ) μm  ( 10 + 27 · L ) μm ( 12,9 + 25 · L ) μm ( 29,4 + 17 · L ) μm ( 58 + 10 · L ) μm	VDI/VDE/DGQ 2618 Part 9.2 L: Measured value (m) r: Resolution
Dial Gauge	L ≤ 30 mm	r: 0,001 mm r: 0,002 mm r: 0,01 mm	( 1,2 + 1 · L ) μm ( 1,8 + 1 · L ) μm ( 8,2 + 1 · L ) μm	VDI/VDE/DGQ 2618 Part 11.1 L: Resolution(m) r: Resolution
Dial Indicator	L ≤ 3 mm	r: 0,01 mm r: 0,002 mm r: 0,001 mm	5,8 μm 1,2 μm 0,7 μm	VDI/VDE/DGQ 2618 Part 11.2 L: Measurement Value(m) r: Resolution
Feeler Gauge	0,01 mm ≤ L ≤ 2 mm		2,0 μm	Thickness Measurement DIN 2275

**Akreditasyon Talep Edilen Kapsamlar (Sayfa 31/31)**

Radius Gauge	$1 \text{ mm} \leq d \leq 25 \text{ mm}$		$3,0 \text{ } \mu\text{m}$	Optical Method d: Measured Value(m)
Height Calipper	$L \leq 300 \text{ mm}$ $300 \text{ mm} < L \leq 600 \text{ mm}$	$r=0,001 \text{ mm}$ $r=0,01 \text{ mm}$ $r=0,02 \text{ mm}$ $r=0,05 \text{ mm}$ $r=0,001 \text{ mm}$ $r=0,01 \text{ mm}$ $r=0,02 \text{ mm}$ $r=0,05 \text{ mm}$	$(5,9 + 16 \cdot L) \text{ } \mu\text{m}$ $(10 + 15 \cdot L) \text{ } \mu\text{m}$ $(12,9 + 13 \cdot L) \text{ } \mu\text{m}$ $(29,4 + 6 \cdot L) \text{ } \mu\text{m}$ $(5,9 + 27 \cdot L) \text{ } \mu\text{m}$ $(10 + 23 \cdot L) \text{ } \mu\text{m}$ $(12,9 + 20 \cdot L) \text{ } \mu\text{m}$ $(29,4 + 12 \cdot L) \text{ } \mu\text{m}$	VDI/VDE/DGQ 2618 Part 9.3 L: Measured Value(m) r: Resolution
Thickness Gauge Lever Gauges for external Measurements	$L \leq 100 \text{ mm}$		$(8,4 + 1 \cdot L) \text{ } \mu\text{m}$	Blok Master ile karşılaştırma yöntemiyle  L: Ölçülen Değer(m)  r: çözünürlük / bölüntü değeri
Dial Gauge	$5 \text{ mm} \leq L \leq 200 \text{ mm}$ $5 \text{ mm} \leq L \leq 100 \text{ mm}$	Outside r: 0,01 mm Outside r: 0,005 mm	$(10 + 11 \cdot L) \text{ } \mu\text{m}$ $(7 + 15 \cdot L) \text{ } \mu\text{m}$	VDI/VDE/DGQ 2618 Bölüm 12.1 VDI/VDE/DGQ 2618 Bölüm
	mm	İnside r: 0,01 mm İnside r: 0,005 mm	$(10 + 11 \cdot L) \text{ } \mu\text{m}$ $(7 + 10 \cdot L) \text{ } \mu\text{m}$	13.1 L: Measured Value (m) r: resolution
Sieve	$L \leq 5 \text{ mm}$	Optical Measurement Method	$3 \text{ } \mu\text{m}$	ISO 3310
	$5 \text{ mm} < L \leq 125 \text{ mm}$	Calipper	$25 \text{ } \mu\text{m}$	ISO 3310
Screw Thread Gauge	$0,35 \text{ mm} \leq L \leq 10 \text{ mm}$		$3 \text{ } \mu\text{m}$	Using Projector Step ve Teeth Height  L: Step

**Akreditasyon Talep Edilen Kapsamlar (Sayfa 31/31)**

Thickness Gauge (Pasometer)	$L \leq 200$ mm	r: 0,01 mm r: 0,001 mm	$(8,3 + 17 \cdot L)$ $\mu\text{m}$ ( $1,4 + 30 \cdot L$ ) $\mu\text{m}$	VDI/VDE/DGQ 2618 Part 10.3  L: Measured Value (m)  r:Resolution
Tape Measure	$0 \text{ mm} < L \leq 3000$ mm $3000 \text{ mm} < L \leq 5000$ mm $5000 \text{ mm} < L \leq 50000$ mm	r: 1 mm	0,4 mm  0,6 mm  $0,5 + 0,12 \cdot L$ mm	Comparision Method / TS 9505  L : Measured Value  r : Resolution

**Volume**

Burette	$1 \text{ mL} \leq V \leq 5 \text{ mL}$  10 mL 25 mL 50 mL 100 mL	Evacuation	3 $\mu\text{L}$  6 $\mu\text{L}$ 10 $\mu\text{L}$ 20 $\mu\text{L}$ 20 $\mu\text{L}$	Procedure written according to TS EN ISO 385  TS ISO 4787 Euramet cg 19 ISO/TR 20461  V: Ölçülen Hacim
---------	--	------------	--	---



**Akreditasyon Talep Edilen Kapsamlar (Sayfa 31/31)**

<b>Volumetric Flask</b>	$1 \text{ mL} \leq V \leq 5 \text{ mL}$ 10 mL 20 mL 25 mL 50 mL 100 mL 200 mL 250 mL 500 mL 1000 mL 2000 mL	<b>Filling</b>	6 $\mu\text{L}$ 10 $\mu\text{L}$ 30 $\mu\text{L}$ 30 $\mu\text{L}$ 35 $\mu\text{L}$ 40 $\mu\text{L}$ 50 $\mu\text{L}$ 50 $\mu\text{L}$ 80 $\mu\text{L}$ 0,2 mL 0,3 mL	Procedure written according to TS 1491 EN ISO 1042 TS ISO 4787 Euramet cg 19 ISO/TR 20461 V: Measured Volume
<b>Graudated Cylinder</b>	5 mL 10 mL 25 mL 50 mL 100 mL 250 mL 500 mL 1000 mL 2000 mL	<b>Filling</b>	6 $\mu\text{L}$ 30 $\mu\text{L}$ 50 $\mu\text{L}$ 60 $\mu\text{L}$ 0,1 mL 0,2 mL 0,4 mL 1 mL 2 mL	Procedure written according to TS EN ISO 4788 TS ISO 4787 Euramet cg 19 ISO/TR 20461
<b>Picnometer</b>	$1 \text{ mL} \leq V \leq 5 \text{ mL}$ $10 \text{ mL} \leq V \leq 100 \text{ mL}$	<b>Filling</b>	6 $\mu\text{L}$ 20 $\mu\text{L}$	Procedure written according to TS ISO 3507 TS ISO 4787 Euramet cg 19 ISO/TR 20461 TS EN ISO 2811

**Akreditasyon Talep Edilen Kapsamlar (Sayfa 31/31)**

<p><b>One Mark Volumetric Pipette</b></p>	<p><math>0,1 \text{ ml} \leq V \leq 5 \text{ mL}</math>  <b>10 mL</b>  <b>20mL</b>  <b>25 mL</b>  <b>50 mL</b>  <b>100 mL</b></p>	<p><b>Evacuation</b></p>	<p><b>3 µL</b>  <b>6 µL</b>  <b>10 µL</b>  <b>10 µL</b>  <b>20 µL</b>  <b>20 µL</b></p>	<p><b>Procedure written according to TS 1489 ISO 648</b>  <b>TS EN ISO 835</b>  <b>TS ISO 4787</b>  <b>Euramet cg 19</b>  <b>ISO/TR 20461</b></p> <p><b>V: Measured Volume</b></p>
<p><b>Piston Pipette</b></p>	<p><b>100 µL</b>  <b>200 µL</b>  <b>500 µL</b>  <b>1 mL</b>  <b>2 mL</b>  <b>5 mL</b>  <b>10 mL</b></p>	<p>Single or multi- channel piston</p> <p>Hand movement or motor driven</p>	<p><b>0,4 µL</b>  <b>0,4 µL</b>  <b>0,6 µL</b>  <b>3 µL</b>  <b>3 µL</b>  <b>6 µL</b>  <b>20 µL</b></p>	<p><b>Procedure written according to TS EN ISO 8655-2</b>  <b>TS EN ISO 8655-6</b>  <b>ISO/TR 20461</b></p> <p><b>V: Measured Volume</b></p>

**Akreditasyon Talep Edilen Kapsamlar (Sayfa 31/31)**

<b>Piston Burette</b>	<b>1 mL 2 mL 5 mL 10 mL 20 mL ≤ V ≤ 50 mL 100 mL</b>	<b>Hand movement or motor driven</b>	<b>0,6 µl 2 µl 3 µl 8 µl 11 µl 20 µl</b>	<b>Procedure written according to TS EN ISO 8655-3 TS EN ISO 8655 -6 ISO/TR 20461 V: Measured Volume</b>
---------------------------	--	--	--	--